COLOR CAMERA KP-D50 REMOTE CONTROL PROTOCOL



- (1) STY: Code indicating the start of TEXT (02)
- (2) TEXT data: Data transmitted and received data as ASCII character code
- (3) ETY: CODE indicating the end of TEXT (03)
- (4) SUM: RESULT OBTAINED BY PERFORMING THE EXCLUSIVE-OR

operation for the sum of all TEXT data and FF as ASCII character code

TEXT Data: 26 BYTES

1 2 3	4 5 6 7	9 9 10 11 12 13 14 15	16 17 19 19 20	21 22 23 24 25 26
No. OF	Διν		Area Relative	
⊳8 1 8	,,,,,	NO.	address No.	

(Detailed format of TEXT data)

(1)	No. of Data:	TEYT bata + 2 bytes (ETY, sum) = 15 bytes
(2)	1D NO. :	Camera ID number set by the user
(3)	Area address:	SET a number for each abjustment item. (O through 255)
		255 (FFH) SHOULD BE & GLOBAL ADDRESS.
(4)	Relative No.:	Set the number determined by each address area.
(5)	Status:	Status information set to the received data.
(6)	Da+a:	Received data is set.

WHEN THE FOLLOWING DATA BLOCK is successively transferred, be sure to provide

a space of more than 100 ms in between a data block and the next bloc.

IF the space is narrow, correct data cannot be transferred to the camera.





Hitachi Kokusai Electric Inc. Head Office 14-20, Higashi-Nakano 3-chrome, Nakana-ku, Tokyo 164-8511, Japan

	Phone : +81 (0) 3-3365-5928, Fax : +81 (0) 3-3365 5929 URL : www.h-kokusai.com		
Hitachi Denshi Head office	(Europa) GmbH Weiskircher Straße 88, D-63110 Rodgau, Germany Phone : +49 6106-69920, Fax : +49 6106-16906 URL : www.hitachi-denshi.de General email address : webmaster@hitachi-denshi.de		
Hitachi Denshi Leeds Office	(Europe) Brookfield House, Selby Road, Garforth, LEEDS, LS25 1NB, United Kingdom Phone : +44 (0)113 287 4400, Fax : +44 (0)113 287 4260 URL : www.hitachi-denshi-uk.com General email address : sales@hitachi-denshi-uk.com		
Hitachi Denshi Head office	(UK) Limited Windsor House, Britannia Road, Waltham Cross, Hertfordshire, EN8 7NX, United Kingdom Phone : +44 (0) 1992 704 595, Fax : +44 (0) 1992 704 599		